



# GoGogate

Det enkla sättet att öppna  
din Crawford garageport



# GoGogate

## Det enkla sättet att öppna din Crawford garageport

GoGogate är ett verkligt smart sätt att förenkla livet vid in- och utgång i ditt garage.

Genom att introducera smartphone-styrning\* till din portautomatik löser du många vardagliga besvär och begränsningar med handsändare, distansöppning samt övervakning av din garageport.

GoGogate är dessutom ännu ett steg för att höja säkerheten vid önskade inbrottsförsök.

\* kompatibel med iOS och Android



100% säker med inbyggd kryptering



Enkel installation



Fjärrstyr via internet



Multipla användare



Portstatus-indikering



Styr tre garageportar med en enhet

### TECHNICAL SPECIFICATION

#### WIRELESS LAN INTERFACE

STANDARD COMPLIANCE	IEEE802.11n, IEEE802.11g, IEEE802.11b Transmission Rates 11n: 150 Mbps 11g: 6/9/12/18/24/36/48/54 Mbps 11b: 1/2/5.5/11 Mbps Channel 1-13
FREQUENCY RANGE	
ANTENNA GAIN	5dBi
SECURITY	WPA2-PSK(TKIP/AES), WPA-PSK(TKIP/AES), 128/64-bit WEP
USB	2.0

APPROVALS  
CE, FCC

#### OUTPUT INTERFACE

OUTPUT TYPE	Volt Free Contact
OUTPUTS	3 relay outputs
MAXIMUM VOLTAGE	60V DC @ 2A
SD CARD	
STANDARD COMPLIANCE	SD Class 4
MEMORY SPACE	4GB
TYPE	SDHC

#### OTHER

DIMENSIONS (WxDxH)	116 x 110 x 29 mm
WEIGHT	approx. 430 g
OPERATING ENVIRONMENT	-10°C to 40°C, 10-90% (non-condensing)
POWER CONSUMPTION	max. 10W
POWER SUPPLY	External AC 100-240V universal, 50/60hz
RF RECEIVER FREQUENCY	433.92 Mhz receiver
MODULATION	OOK
RANGE	approx. 50m or 150ft (outdoors)